DESCRIPTION

SWITCHED CAPACITOR FILTER AND FEEDBACK SYSTEM

5 TECHNICAL FIELD

[0001] The present invention relates to switched capacitor filters, and more particularly relates to technique for a switched capacitor filter suitable for a loop filter in a feedback system such as a phase-locked loop and a delay locked loop.

10 BACKGROUND ART

[0002] Today, the number of functions provided in a system LSI has been increased and the circuit size of system LSIs tends to be increased. Thus, reduction in the circuit size of system LSIs has been a universal issue.

[0003] In almost all LSIs, a phase-locked loop (which will be hereafter referred to as a

15 "PLL") is provided. As for PLLs, there is the restriction that a maximum value of a response time can not be made to be equal to or larger than about one-tenth of a frequency of an input clock. Therefore, a CR product of a loop filter constituting a PLL has to be set to be relatively large. To achieve a relatively large CR product, in general, a capacitance value of a capacitor constituting a loop filter is set to be large. Accordingly, among

20 components of the PLL, the loop filter occupies a larger portion of a circuit area of the PLL. Since the lower a frequency of an input clock in the PLL is, the larger a response time becomes, the capacitance value of the capacitor constituting the loop filter has to be set even larger. As a result, the circuit size of the PLL is increased. To solve such problems, reduction in the circuit size of loop filters is desired.

25 [0004] As a technique for reducing the circuit size of a loop filter used in a PLL, there is a

technique disclosed in Japanese Patent Application No. 2003-185573 by the first inventor of the present application et al. FIG. **16** is a block diagram illustrating a configuration of a loop filter according to the invention (which will be hereafter referred to as "prior application") disclosed in the specification of Japanese Patent Application No. 2003-

5   185573. The loop filter includes a capacitor **310** (capacitance value **C**) connected to an input terminal **IN1**, a resistor **320** (resistance value **R**) and a capacitor **330** (capacitance value C_3) which are connected to an input terminal **IN2**, and a voltage buffer circuit **350** provided between the capacitor **310** and the resistor **320**. Discharge/charge currents (charge currents) **Ip1** and **Ip2** are supplied to the input terminals **IN1** and **IN2**,

10 respectively, from a dual charge pump circuit. Then, the loop filter outputs a voltage **Vout** generated at a connection point of the resistor **320** and the capacitor **330**. In the loop filter, with a current supplied to the capacitor **310** set to be smaller than a current supplied to the resistor **320**, only a capacitance value of the capacitor **310** is reduced without increasing a resistance value of the resistor **320**. Thus, the same CR product as that of a known loop

15 filter, i.e., the same filter characteristics as those of the known loop filter can be realized. Moreover, because a sufficient voltage is applied to each of the capacitors **310** and **330**, it is possible to realize use of a MOS capacitor as each of the capacitors. Thus, respective sizes of the capacitors **310** and **330** are reduced, so that the entire circuit size of the loop filter is reduced.

20 [0005] The loop filter has to be configured so that a sufficiently large voltage is generated in the resistor **320**. Therefore, a current value of a current flowing in the resistor **320** has to be set to be relatively large or a resistance value of the resistor **320** has to be set to be relatively large. However, each of those cases is not preferable because power consumption of the resistor **320** becomes relatively large in either case. Specifically, since

25 the resistor **320** becomes a cause of the generation of noise, it is preferable to avoid

increasing the resistance value of the resistor **320**.

[0006] To reduce noise caused due to a resistor in a loop filter, a loop filter including, instead of a resistor, a switched capacitor circuit has been well known (see, for example, Patent Reference 1). FIG. **17** is a block diagram illustrating a configuration of a known loop filter including a switched capacitor circuit. The loop filter includes capacitors **310** (capacitance value **C**) and **330** (capacitance value C_3) connected to an input terminal **IN** and a switched capacitor circuit **320A** connected to the capacitor **310**. The loop filter outputs a voltage **Vout** generated at a connection point of the capacitors **310** and **330**. The switched capacitor circuit **320A** includes a capacitor **340** (capacitance value C_R) and switches **Q1** and **Q2** for switching a connection direction of the capacitor **340**. The switched capacitor circuit **320A** substantially exhibits a resistance value **R**. In the above-described configuration, a resistor is omitted from a loop filter, so that noise caused due to the resistor can be reduced.

Patent Reference 1: United States Patent No. 6420917, specification, (pp. 6-7, FIG. 4).

DISCLOSURE OF INVENTION

PROBLEMS THAT THE INVENTION IS TO SOLVE

[0007] As has been described, the loop filter according to the prior application has a problem in which power consumption is relatively large while a circuit size is reduced. Moreover, to realize the capacitor **310** using a MOS capacitor, the voltage buffer circuit **350** has to be provided, but the voltage buffer circuit **350** causes the generation of noise. For those reasons, it is preferable to omit the voltage buffer circuit **350**.

[0008] On the other hand, considering a known loop filter including a switched capacitor circuit, the known loop filter does not include a resistor and a voltage buffer circuit. Thus, noise caused by those components is not a problem. However, the capacitor **310** is still

relatively large as in a known technique, and reduction in the circuit size is difficult. Moreover, when the switch **Q1** is turned ON, the capacitor **340** is connected with the capacitor **310** in series and it is difficult to apply a sufficient voltage to the capacitor **340**. Therefore, it is difficult to realize the capacitor **340** using a MOS capacitor. This is because a larger voltage than a threshold of a MOS transistor constituting a MOS capacitor has to be applied to the MOS transistor.

[0009] In view of the above-described problems, it is an object of the present invention to reduce a circuit size of a switched capacitor filter including a switched capacitor circuit. Particularly, it is another object of the present invention to provide a switched capacitor filer in which, instead of providing a voltage buffer circuit, each capacitor is formed of a MOS capacitor.

SOLUTION TO THE PROBLEMS

[0010] As means for achieving the above-described objects according to the present invention, a switched capacitor filter for receiving a current signal and outputting a voltage signal has been devised. The inventive switched capacitor filter includes a first capacitor provided between an input terminal for the current signal and a reference voltage; a switched capacitor circuit provided between the input terminal and the first capacitor; and a second capacitor provided in parallel to the first capacitor and the switched capacitor circuit.

[0011] Thus, the switched capacitor circuit functions as a resistor, so that the switched capacitor filter is operated as a passive-type secondary low-pass filter. Normally, the switched capacitor circuit is formed of one or more capacitors. Accordingly, the switched capacitor filter includes only capacitors. The switched capacitor circuit is provided between the input terminal and the first capacitor. Thus, when a capacitor in the switched

capacitor circuit is connected to an input terminal side, a sufficiently large voltage is applied to the capacitor. Therefore, a capacitance of the capacitor can be reduced. As a result, a circuit size of the entire switched capacitor filter can be reduced.

[0012] Specifically, the switched capacitor circuit includes first and second terminals, third and fourth capacitors each having one end to which a reference voltage is supplied and substantially the same capacitance, and a switching section for switching a connection state between the other end of each of the third and fourth capacitors and an associated one of the first and second terminals. When the switching section connects the other end of the third capacitor to the first terminal, the switching section connects the other end of the fourth capacitor to the second terminal, and when the switching section connects the other end of the third capacitor to the second terminal, the other end of the fourth capacitor to the first terminal. The capacitance of the second capacitor is larger than respective capacitances of the third and fourth capacitors.

[0013] In the above-described manner, with the capacitance of the second capacitor set to be larger than the respective capacitances of the third and fourth capacitors in the switched capacitance circuit, the switched capacitor filter has the same filter characteristics as those of a typical passive-type secondary low-pass filter.

[0014] Each of the first through fourth capacitors is preferably a MOS capacitor.

[0015] Specifically, the switched capacitor circuit includes a first terminal provided on a side of the first capacitor, a second terminal provided on a side of the input terminal, a plurality of capacitors each having one end to which a reference voltage is supplied and substantially the same capacitance, and a switching section for switching a connection state between the other end of each of the plurality of capacitors and an associated one of the first and second terminals. While maintaining connection between the other end of one of the plurality of capacitors and the second terminal, when the switching section connects the

other end of one of other two of the plurality of capacitors to the first terminal, the switching section connects the other end of the other one of the other two to the second terminal.

[0016] Each of the first and second capacitors and the plurality of capacitors is preferably a MOS capacitor.

[0017] As another means according to the present invention, a feedback system for feeding back an output clock generated on the basis of an input clock to make the output clock have a predetermined characteristic has been devised. The feedback system includes: a charge pump circuit for generating a charge current, on the basis of a phase difference between the input clock and a fed-back clock; a loop filter for receiving the charge current as an input; and an output clock generator circuit for generating the output clock, on the basis of an output signal from the loop filter. The loop filter includes a first capacitor provided between an input terminal for the charge current and a reference voltage, a switched capacitor circuit provided between the input terminal and the first capacitor, and a second capacitor provided in parallel to the first capacitor and the switched capacitor circuit.

[0018] Thus, the switched capacitor circuit functions as a resistor, so that the loop filter is operated as a passive-type secondary low-pass filter. Normally, the switched capacitor circuit is formed of one or more capacitors. Accordingly, the loop filter includes only capacitors. The switched capacitor circuit is provided between the input terminal and the first capacitor. Thus, when a capacitor in the switched capacitor circuit is connected to an input terminal side, a sufficiently large voltage is applied to the capacitor. Therefore, a capacitance of the capacitor can be reduced. As a result, a circuit size of the entire loop filter and, furthermore, a circuit size of the entire feedback system can be reduced.

[0019] Specifically, the switched capacitor circuit includes first and second terminals,

third and fourth capacitors each having one end to which a reference voltage is supplied and substantially the same capacitance, and a switching section for switching a connection state between the other end of each of the third and fourth capacitors and an associated one of the first and second terminals. When the switching section connects the other end of the

5   third capacitor to the first terminal, the switching section connects the other end of the fourth capacitor to the second terminal, and when the switching section connects the other end of the third capacitor to the second terminal, the other end of the fourth capacitor to the first terminal, and the capacitance of the second capacitor is larger than respective capacitances of the third and fourth capacitors.

10   [0020] Specifically, the feedback system further includes a control clock generator circuit for generating, on the basis of a falling of the input clock, first and second control clocks having an inverse correlation with each other and third and fourth control clocks corresponding to inverse clocks of the first and second control clocks, respectively. The switching section includes a switch for switching a connection state between the other end

15   of the third capacitor and the first terminal according to the first control clock, a switch for switching a connection state between the other end of the fourth capacitor and the first terminal according to the second control clock, a switch for switching a connection state between the other end of the third capacitor and the second terminal according to the third control clock, and a switch for switching a connection state between the other end of the

20   fourth capacitor and the second terminal.

[0021] In this manner, with the capacitance of the second capacitor set to be larger than respective capacitances of the third and fourth capacitors in the switched capacitance circuit, the loop filter has the same filter characteristics as those of a typical passive-type secondary low-pass filter.

25   [0022] Each of the first through fourth capacitors is preferably a MOS capacitor.

[0023] Specifically, in the feedback system, the switched capacitor circuit includes a first terminal provided on a side of the first capacitor, a second terminal provided on a side of the input terminal, a plurality of capacitors each having one end to which a reference voltage is supplied and substantially the same capacitance, and a switching section for switching a connection state between the other end of each of the plurality of capacitors and an associated one of the first and second terminals. While maintaining connection between the other end of one of the plurality of capacitors and the second terminal, when the switching section connects the other end of one of other two of the plurality of capacitors to the first terminal, the switching section connects the other end of the other one of the two to the second terminal.

[0024] Specifically, the feedback system further includes a control clock generator circuit for generating, on the basis of a falling of the input clock, a plurality of control clocks having different phases from each other and the number of the plurality of control clocks corresponds to the number of the plurality of capacitors and a plurality of inversion control clocks corresponding to inversed clocks of the plurality of control clocks. The switching section includes a plurality of switches, provided so as to correspond to the plurality of capacitors, respectively, each switching a connection state between the other end of an associated one of the plurality of capacitors and the first terminal according to one of the plurality of control clocks corresponding to the associated one of the plurality of capacitors, and a plurality of switches, provided so as to correspond to the plurality of capacitors, respectively, each switching a connection state between the other end of an associated one of the plurality of capacitors and the second terminal according to one of the plurality of control clocks corresponding to the associated one of the plurality of capacitors.

[0025] Each of the first and second capacitors and the plurality of capacitors is preferably

a MOS capacitor.

EFFECTS OF THE INVENTION

[0026] As has been described, according to the present invention, a switched capacitor filter which has the same filter characteristics as those of a known technique and a reduced circuit size can be obtained. The switched capacitor filter does not include a resistor and a voltage buffer circuit but includes only capacitors. Thus, with a reduced input current, a size of each of the capacitors is reduced and a circuit size as a whole can be reduced. Furthermore, when the switched capacitor is used as a loop filter of a feedback system, a size of a charge pump circuit can be reduced by reducing a charge current which is an input current of the loop filter. As a result, a circuit size of an entire feedback system can be largely reduced.

BRIEF DESCRIPTION OF DRAWINGS

[0027] [FIG.1] FIG. 1 is a block diagram illustrating a configuration of a phase-locked loop according to a first embodiment of the present invention.

[FIG. 2] FIG. 2 is a block diagram illustrating a configuration of a control clock generator circuit in the phase-locked loop of FIG. 1.

[FIG. 3] FIG. 3 is a timing chart for the control clock generator circuit of FIG. 2.

[FIG. 4] FIG. 4 is a block diagram illustrating a configuration of a loop filter in the phase-locked loop of FIG. 1.

[FIG. 5] FIG. 5 is a block diagram illustrating a configuration of a loop filter obtained by merely replacing a resistor in a loop filter according to the prior application with a switched capacitor circuit.

[FIG. 6] FIG. 6 is a block diagram illustrating a configuration of a loop filter obtained by

changing the switched capacitor circuit in the loop filter of FIG. 5 to a three-phase clock controlled switched capacitor circuit.

[FIG. 7] FIG. 7 is a block diagram illustrating a configuration of a loop filter obtained by changing the switched capacitor circuit in the loop filter of FIG. 6 to a two-phase clock controlled switched capacitor circuit.

[FIG. 8] FIG. 8 is a block diagram illustrating a configuration of a loop filter obtained by omitting a voltage buffer circuit in the loop filter of FIG. 7.

[FIG. 9] FIG. 9 is a block diagram illustrating a configuration of a loop filter obtained by changing the loop filter of FIG. 8 to a single charge current input.

[FIG. 10] FIG. 10 is a block diagram illustrating a configuration of a control clock generator circuit for generating each control clock, on the basis of a reset pulse from a phase comparator.

[FIG. 11] FIG. 11 is a timing chart for the control clock generator circuit of FIG. 10.

[FIG. 12] FIG. 12 is a block diagram illustrating a configuration of a phase-locked loop according to a second embodiment of the present invention.

[FIG. 13] FIG. 13 is a block diagram illustrating a configuration of a control clock generator circuit in the phase-locked loop of FIG. 12.

[FIG. 14] FIG. 14 is a timing chart for the control clock generator circuit of FIG. 13.

[FIG. 15] FIG. 15 is a block diagram illustrating a configuration of a loop filter in the phase-locked loop of FIG. 12.

[FIG. 16] FIG. 16 is a block diagram illustrating a configuration of a loop filter according to the prior application by the first inventor of the present invention et al.

[FIG. 17] FIG. 17 is a block diagram illustrating a configuration of a known loop filter including a switched capacitor circuit.

EXPLANATION OF REFERENCE NUMERALS

[0028]   31   MOS capacitor (first capacitor)

32, 32A   Switched capacitor circuit

33   MOS capacitor (second capacitor)

321   MOS capacitor (third capacitor, one of a plurality of capacitors)

322   MOS capacitor (fourth capacitor, one of the plurality of capacitors)

323   MOS capacitor (one of the plurality of capacitors)

324, 324A   Switching section

20   Charge pump circuit

30, 30A   Loop filter

40   Voltage control oscillator (output clock generator circuit)

60, 60', 60A   Control clock generator circuit

T1   Terminal (first terminal)

T2   Terminal (second terminal)

SW11, SW12, SW21, SW22, SW31, SW32 Switch

$\varphi 1$ Control clock (first control clock, one of a plurality of control clocks)

$\varphi 2$ Control clock (second control clock, one of the plurality of contro-clocks)

$\varphi 3$ Control clock (one of the plurality of control clocks)

$/\varphi 1$ Control clock (third control clock, one of a plurality of inversion control clocks)

$/\varphi 2$ Control clock (fourth control clock, one of the plurality of inversion control clocks)

$/\varphi 3$ Control clock (one of the plurality of inversion control clocks)

CKin   Input clock

CKout Output clock

BEST MODE FOR CARRYING OUT THE INVENTION

5   [0029] Hereafter, best mode for carrying out the present invention will be described with reference to the accompanying drawings.

[0030]   (First Embodiment)

FIG. 1 illustrates a configuration of a PLL according to a first embodiment of the present invention. The PLL of this embodiment includes a phase comparator **10**, a charge

10   pump circuit **20**, a loop filter (LPF) **30**, a voltage control oscillator (VCO) **40** as an output clock generator circuit, a frequency divider **50** and a control clock generator circuit **60**. The phase comparator **10** compares a phase of an input clock **CKin** supplied to the PLL with a phase of a feedback clock **CKdiv** and outputs an up signal **UP** and a down signal **DN** according to a difference between the phases. The charge pump circuit **20** outputs

15   (discharges or charges), on the basis of the up signal **UP** and the down signal **DN**, a charge current **Ip**. The voltage control oscillator **40** changes, on the basis of the voltage **Vout** output from the loop filter **30**, a frequency of the output clock **CKout** of the PLL. The frequency divider **50** frequency-divides the output clock **CKout** by N (N is a natural number) and feeds back the frequency-divided output clock as the feedback clock **CKdiv**

20   to the phase comparator **10**. While the above-described operations are repeated, the output clock **CKout** gradually converges to a predetermined frequency and is locked. Hereafter, configurations and operations of the loop filter **30** and the control clock generator circuit **60** will be described in detail.

[0031] The control clock generator circuit **60** generates, on the basis of the input clock

25   **CKin**, control clocks φ1, /φ1, φ2 and /φ2 and outputs the control clocks to the loop filter

30. FIG. 2 is a block diagram illustrating a configuration of the control clock generator circuit **60**. Moreover, FIG. 3 is a timing chart for the control clock generator circuit **60**. An inverter **61** inverts the input clock **CKin** and outputs a clock **/CKin**. A D flipflop **62** outputs a clock **CKorg** which synchronizes with a rising of the clock **/CKin** and of which a polarity is inverted and a clock **/CKorg** which is inversion of the clock **CKorg**. A circuit section including an inverter **631** and NAND gates **641** and **651** generates a control clock φ1 and a control clock /φ1 which is inversion of the control clock φ1, on the basis of the clock **/CKorg**. A circuit section including an inverter **632** and NAND gates **642** and **652** generates a control clock φ2 and a control clock /φ2 which is inversion of the control clock φ2, on the basis of the clock **CKorg**. That is, the control clock generator circuit **60** outputs control clocks φ1, /φ1, φ2 and /φ2 of which respective polarities are inverted according to a falling of the input clock **CKin**.

[0032] The loop filter **30** receives the charge current **Ip**, smoothes a voltage generated due to the charge current **Ip** and outputs the generated voltage as a voltage **Vout**. FIG. **4** illustrates a circuit configuration of the loop filter **30**. The loop filter **30** includes a MOS capacitor **31**, a switched capacitor circuit **32** and an MOS capacitor **33**. One end of the MOS capacitor **31** is connected to a ground as a reference voltage and the other end of the MOS capacitor **31** is connected to a terminal **T1** of the switched capacitor circuit **32**. One end of the MOS capacitor **33** is connected to the ground as a reference voltage and the other end of the MOS capacitor **33** is connected to an input terminal for the charge current **Ip** and a terminal **T2** of the switched capacitor circuit **32**. The loop filter **30** outputs a voltage **Vout** generated in a connection point of the switched capacitor circuit **32** and the MOS capacitor **33**.

[0033] The switched capacitor circuit **32** is a so-called P. S. (parasitic sensitive) type which includes MOS capacitors **321** and **322** and a switching section **324** for switching

connection states of the MOS capacitors 321 and the MOS capacitor 322 with the terminals T1 and T2. The switching section 324 includes a switch SW11 for switching a connection state between the MOS capacitor 321 and the terminal T1 according to the control clock $\varphi 1$, a switch SW12 for switching a connection state between the MOS capacitor 321 and

5 the terminal T2 according to the control clock $/\varphi 1$, a switch SW21 for switching a connection state between the MOS capacitor 322 and the terminal T1 according to the control clock $\varphi 2$ and a switch SW22 for switching a connection state between the MOS capacitor 322 and the terminal T2 according to the control clock $/\varphi 2$. Note that the control clocks $\varphi 1$, $/\varphi 1$, $\varphi 2$ and $/\varphi 2$ are supplied from the control clock generator circuit 60.

10 [0034] A capacitance value of the MOS capacitor 31 is C. The capacitance value C is equivalent to the capacitance value of the capacitor 310 in the loop filter of the prior application (see FIG. 16). Each of respective capacitance values of the MOS capacitors 321 and 322 is C_R. A resistance value exhibited by the switched capacitor circuit 32 is R. The resistance R is equivalent to the resistance value of the resistor 320 in the loop filter of

15 the prior application. Assume that an operation frequency of each of the switches SW11, SW12, SW21 and SW22 in the switched capacitor circuit 32 is f_{clk}. The equation of $R = 1/(f_{clk}C_R)$ holds. That is, to increase the resistance value of the switched capacitor circuit 32, the respective capacitances of the MOS capacitors 321 and 322 are reduced. As has been described, when the charge current Ip supplied to the loop filter 30 is intended to

20 be reduced, the resistance value of the switched capacitor circuit 32 has to be increased. Then, when the resistance of the switched capacitor circuit 32 is intended to be increased, the respective capacitances of the MOS capacitors 321 and 322 are reduced. That is, reduction in circuit size of each of the MOS capacitors 321 and 322 is achieved by reducing the charge current Ip. Also, with the charge current Ip reduced, the size of each

25 of the MOS capacitors 31 and 33 is reduced. As a result, the circuit size of the entire loop

filter **30** is reduced.

[0035] A capacitance value of the MOS capacitor **33** is C_X. The capacitance value C_X corresponds to a total of the capacitance value C_R of each of the MOS capacitors **321** and **322** and a capacitance value C_3 of the capacitor **330** in the loop filter of the prior application. When the capacitance value C_3 is about 1/5-1/6 of a capacitance value C of the MOS capacitor **31** at largest, the most stable response can be obtained. Details about this is described, for example, in Reference: F. M. GARDNER, "CHARGE-PUMP PHASE-LOCKEDLOOPS", IEEE TRANS., VOL. COM-28, PP. 1849-1858, NOV. 1980.

[0036] When a phase of the input clock **CKin** precedes a phase of the output clock **CKout**, one of output signals of the phase comparator **10** in the PLL of FIG. **1**, for example, a signal **UP** becomes a predetermined logic level, ex., "H" (see FIG. **3**) in a period from a rising of the input clock **CKin** to a rising of the output clock **CKout**. While the signal **UP** is "H, the charge current **Ip** is output from the charge pump circuit **20** to the loop filter **30**. While the charge current **Ip** is received, an operation state of the switching section **324** must not be changed. If the operation state of the switching section **324** is changed, there might be cases where discharge/charge of charges to the MOS capacitors **321** and **322** in the switched capacitor circuit **32** is interrupted and the loop filter **30** is not normally operated. As for the control clocks φ1, /φ1, φ2 and /φ2 generated by the control clock generator circuit **60** of this embodiment, their polarities are not inverted in a period from a falling of the input clock **CKin** to a next falling thereof. Therefore, discharge and charge of charges to the MOS capacitors **321** and **322** are not interrupted. In any case, outputting of each of the signals **UP** and **DN** is completed during continuous falling of the input clock **CKin**. Accordingly, by controlling the operation of the switched capacitor circuit **32**, on the basis of each control clock generated by the control clock generator circuit **60**, a normal operation of the loop filter **30** is ensured.

[0037] Next, the loop filter **30** having the same filter characteristics as those of a general active-type secondary loop filter will be explained while describing what modification is made to the circuit configuration of the loop filter of the prior application to obtain the loop filter **30**. FIG. **5** is a block diagram illustrating a configuration of a loop filter obtained by merely replacing the resistor in the loop filter of the prior application with a switched capacitor circuit. The loop filter obtained by merely replacing the resistor in the loop filter of the prior application with the two-phase clock controlled switched capacitor circuit **32** is not normally operated. The reason for this is as follows. After discharge/charge by the charge current **Ip** for one of the MOS capacitors **321** and **322** connected to an input side of a charge current **Ip2** has been completed, respective polarities of the control clocks $\varphi 1$ and $\varphi 2$ are inverted and the MOS capacitor is connected to a voltage buffer circuit **35** side. When the connection is provided, the MOS capacitor is reset to be a potential of an output terminal of the voltage buffer circuit **35**. As a result, the switched capacitor circuit **32** might not be normally operated and misoperation of the loop filter **30** might be caused. Note that the following description will be made on the assumption that the charge currents **Ip1** and **Ip2** are the same in current size.

[0038] To solve the above-described problems, charges discharge/charged by the charge current **Ip** have to be maintained in a period corresponding to at least one clock cycle of the control clock $\varphi 1$ or $\varphi 2$. Therefore, use of a three-phase clock controlled switch capacitor circuit will be considered. FIG. **6** is a block diagram illustrating a configuration of a loop filter obtained by changing the switched capacitor circuit in the loop filter of FIG. **5** to a three-phase clock controlled switched capacitor circuit. In the switched capacitor circuit **32A**, a connection state between one of the capacitors **321**, **322** and **323** connected to the MOS capacitor **33** and the MOS capacitor **33** is maintained, even when respective connection states of the other two are switched to different states. Thus, the capacitor is

not reset to a buffer potential, so that a normal operation of the switched capacitor circuit 32A is ensured. The loop filter will be later described in detail.

[0039] In the switched capacitor circuit 32A, when connection states of two of the capacitors 321, 322 and 323 are switched, connection between the other one of the capacitors 321, 322 and 323 and the MOS capacitor 33 is maintained. This is like a state where the MOS capacitor 33 and a capacitor having a capacitance value C_R are constantly connected to each other in parallel. Therefore, by increasing the capacitance value of the MOS capacitor 33 by the capacitance value C_R of each of the capacitors 321, 322 and 323 in the switched capacitor circuit 32A, a two-phase clock controlled switched capacitor circuit can be used, instead of the three-phase clock controlled switched capacitor circuit 32A. That is, replacement with the switched capacitor circuit 32 of FIG. 5 can be achieved. FIG. 7 is a block diagram illustrating a configuration of a loop filter obtained by changing the switched capacitor circuit in the loop filter of FIG. 6 to a two-phase clock controlled switched capacitor circuit. The loop filter of FIG. 7 is different from the loop filter of FIG. 5 in that in contrast to a capacitance value of the MOS capacitor 33 is C_3 in the loop filter of FIG. 5, a capacitance value of the MOS capacitor 33 in FIG. 7 is $C_3 + C_R$.

[0040] In general, a voltage buffer circuit is connected to a power supply source and thus there might be cases where noise is transmitted to a loop filter via the power supply source. The voltage buffer circuit itself consumes electric power. Therefore, it is preferable to omit the voltage buffer circuit 35. Then, removal of the voltage buffer circuit 35 from the loop filter of FIG. 7 will be considered. FIG. 8 is a block diagram illustrating a configuration of a loop filter obtained by omitting a voltage buffer circuit in the loop filter of FIG. 7. When the voltage buffer circuit 35 is removed from the loop filter of FIG. 7, the MOS capacitor 31 is discharged/charged by a resultant value of the charge currents Ip1 and Ip2. Thus, a speed of discharge/charge becomes doubled. Therefore, the capacitance

value of the MOS capacitor **31** is made to be doubled, i.e., **2C** so that an equivalent discharge/charge speed to that in the case where the voltage buffer circuit **35** is provided is achieved.

[0041] Furthermore, providing a single charge current input in the loop filter of FIG. **8** will be considered. FIG. **9** is a block diagram illustrating a configuration of a loop filter obtained by changing the loop filter of FIG. **8** to a single charge current input. In the loop filter of FIG. **8**, the MOS capacitor **31** is discharged/charged by a resultant value of the charge currents **Ip1** and **Ip2**. Thus, to achieve a single charge current input, a current value of the charge current is made to be a current value (2Ip2 corresponding to the double of the charge current **Ip2** in this case) corresponding to the resultant value of the charge currents **Ip1** and **Ip2**. Accordingly, each of respective capacitance values of the capacitors **321** and **322** and a capacitance value of the MOS capacitor **33** in the switched capacitor circuit **32** is made to be doubled.

[0042] The loop filter of FIG. **9** has a circuit configuration obtained by doubling a capacitance value and a charge current value of each capacitor in the loop filter **30** of this embodiment shown in FIG. **4**. That is, the loop filter of FIG. **9** has substantially the same circuit configuration as that of the loop filter **30** and has the same filter characteristics as those of a general active-type secondary loop filter.

[0043] As has been described, according to this embodiment, a loop filter can be formed not to include a resistor and a voltage buffer circuit but include only MOS capacitors. Thus, a circuit size can be reduced while noise and power consumption are reduced. Moreover, with the charge current **Ip** set to be relatively small, a circuit size of the charge pump circuit **20** can be reduced. As a result, a circuit size of the entire PLL can be largely reduced.

[0044] Note that the control clocks φ1, /φ1, φ2 and /φ2 may be generated on the basis of a

reset pulse in the phase comparator **10**. FIG. **10** is a block diagram illustrating a configuration of a control clock generator circuit **60'** for generating each control clock, on the basis of a reset pulse **RST** from the phase comparator **10**. FIG. **11** is a timing chart for the control clock generator circuit **60'**. The reset pulse **RST** is output from a NAND gate

5   **13** in the phase comparator **10** including D flipflops **11** and **12** and the NAND gate **13**. That is, the reset pulse **RST** is a pulse with a very short duty and is output after the signal **UP** or **DN** is output. The control clock generator circuit **60'** receives a reset pulse **RST**, instead of an inversion of the input clock **CKin**, generates, on the basis of the reset pulse **RST**, the control clocks φ1, /φ1, φ2 and /φ2 and then outputs the control clocks φ1, /φ1,

10   φ2 and /φ2. As described above, the reset pulse **RST** is a pulse to be output after outputting the signal **UP** or **DN**, and thus the polarity of each of the control clocks is not inverted while the signal **UP** or **DN** is output. However, a pulse width of the reset pulse **RST** is very small and therefore there might be cases where the D flipflop **62** does not respond to an input of the reset pulse **RST**. In such a case, the switched capacitor circuit

15   **32** in the loop filter **30** is not normally operated. Therefore, it is more preferable to use the control clock generator circuit **60** than to use the control clock generator circuit **60'**.

[0045] (Second Embodiment)

FIG. **12** is a block diagram illustrating a configuration of a PLL according to a second embodiment of the present invention. The PLL of this embodiment includes a

20   phase comparator **10**, a charge pump circuit **20**, a loop filter **30A**, a voltage control oscillator **40**, a frequency divider **50** and a control clock generator circuit **60A**. Of these components, the phase comparator **10**, the charge pump circuit **20**, the voltage control oscillator **40** and the frequency divider **50** are the same as those described in the first embodiment and therefore the description thereof will be omitted. Hereafter,

25   configurations and operations of the loop filter **30A** and the control clock generator circuit

60A will be described in detail.

[0046] The control clock generator circuit **60A** generates control clocks φ1, /φ1, φ2, /φ2, φ3 and /φ3, on the basis of an input clock **CKin**, and outputs these control clocks to the loop filter **30A**. FIG. **13** is a block diagram illustrating a configuration of the control clock generator circuit **60A**. FIG. **14** is a timing chart for the control clock generator circuit **60A**. An inverter **61** inverts the input clock **CKin** and output a clock /**CKin**. D flipflops **621**, **622**, **623** and **624** are synchronized with a rising of the clock /**CKin** and are operated. An output of each of the D flipflops **621** and **622** is an input of a NOR gate **66**. An output of the NOR gate **66** is a data input of the D flipflop **621**. A circuit section including the inverter **631** and NAND gates **641** and **651** generates a control clock φ1 and a control clock (inversion control clock) /φ1 which is inversion of the control clock φ1, on the basis of an inversion output from the D flipflop **622**. A circuit section including an inverter **632** and NAND gates **642** and **652** generates the control lock φ2 and a control clock (inversion control clock) /φ2 which is inversion of the control clock φ2, on the basis of an inversion output from the D flipflop **623**. Then, a circuit section including an inverter **633** and NAND gates **643** and **653** generates a control clock φ3 and a control clock (inversion control clock) /φ3 which is inversion of the control clock φ3, on the basis of an inversion output from the D flipflop **624**. The control clocks φ1, φ2 and φ3 output from the control clock generator circuit **60A** having the above-described configuration are different from one another. That is, the control clock generator circuit **60A** generates different control clocks of three different phases, on the basis of the input clock **CKin**.

[0047] FIG. **15** is a block diagram illustrating a configuration of the loop filter **30A**. The loop filter **30A** is obtained by omitting the voltage buffer circuit **35** from the loop filter of FIG. **6** and changing the charge current input to a signal charge current input.

[0048] The switched capacitor circuit **32A** includes MOS capacitors **321**, **322** and **323** and

a switching section **324A** for switching connection states of the MOS capacitors **321, 322** and **323** with terminals **T1** and **T2**. The switching section **324A** includes a switch **SW11** for switching a connection state between the MOS capacitor **321** and the terminal **T1** according to the control clock φ1, a switch **SW12** for switching a connection state between the MOS capacitor **321** and the terminal **T2** according to the control clock /φ1, a switch **SW21** for switching a connection state between the MOS capacitor **322** and the terminal **T1** according to the control clock φ2, a switch **SW22** for switching a connection state between the MOS capacitor **322** and the terminal **T2** according to the control clock /φ2, a switch **SW31** for switching a connection state between the MOS capacitor **323** and the terminal **T1** according to the control clock φ3 and a switch **SW32** for switching a connection state between the MOS capacitor **323** and the terminal **T2** according to the control clock /φ3.

[0049] When connection directions of two of the MOS capacitors **321** through **323** in the switched capacitor circuit **32A** are switched, the other of the MOS capacitors **321** through **323** is kept connected with the MOS capacitor **33**. For example, when a polarity of each of the control clocks φ1, /φ1, φ2 and /φ2 is inverted, a logic level of the control clock /φ3 is kept to be "H" (see FIG. **14**). That is, when connection directions of the MOS capacitors **321** and **322** are changed, the MOS capacitor **323** is continuously connected to the MOS capacitor **33** in parallel. Accordingly, charge discharged/charged from/to the MOS capacitor **323** is not reset, so that a normal operation of the switched capacitor circuit **32A** is ensured.

[0050] As has been described, according to this embodiment, the loop filter including only MOS capacitors without using a resistor and a voltage buffer circuit. Thus, a circuit size is reduced while noise and power consumption are reduced. Moreover, with the charge current **Ip** set to be relatively small, a circuit size of the charge pump circuit **20** can be

reduced. As a result, a circuit size of the entire PLL can be largely reduced.

[0051] Note that, instead of the switched capacitor circuit **32A**, a four- or more- clock controlled switched capacitor circuit may be provided. In such a case, respective connection states of the MOS capacitors are controlled so that connection between one of the MOS capacitors and the MOS capacitor **33** is maintained and respective connection directions of the other ones of the MOS capacitors in the switched capacitor circuit are switched.

[0052] In each of PLL of FIG. **1** and PLL of FIG. **12**, instead of the voltage control oscillator **40**, a voltage control delay circuit (VCD) as an output clock generator circuit is provided, the frequency divider **50** is omitted and the output clock **CKout** output by the control delay circuit is directly fed back to the phase comparator **10**. Thus, a delay locked loop (DLL) is constituted.

INDUSTRIAL APPLICABILITY

[0053] A switched capacitor filter according to the present invention has the same filter characteristics as those of a known filter and has a reduced circuit size. Thus, in microprocessor including many PLLs, the switched capacitor filter is useful as a loop filter in each of the PLLs. Also, in a semiconductor integrated circuit of which a circuit size is limited, for example, an IC card on which a large capacitor is difficult to mount, the switched capacitor filter of the present invention is useful as a loop filter of each PLL.